


Tuning Guide for CELmar0T

457-0007.02



Center Frequency [MHz]	+/- 3 MHz Bandwidth	Length. L [mm]
144	141-147	1095
148	145-151	1035
152	149-155	980
156	153-159	930
160	157-163	880
164	161-167	835
168	165-171	795
172	169-175	755
176	173-179	720

1. Cut the antenna's whip to length based on desired center frequency, a +/- 3MHz performance bandwidth is given from that length.
2. Length may vary from provided values depending on actual installed location.

CELmar0T Tune Plot

